














# Selection Guide



Key Features		iMeter 5	iMeter 6	iMeter 7A	iMeter 8	iMeter D7
General	Class (kWh)	0.2S	0.2S	0.2S	0.2S	0.2S
	Dimensions (WxHxD/mm)	 96x96x85	 96x96x119.5	 144x144x128	 192x192x182.4	 145x124x77
	Display (Backlit)	Color IPS 320x240 (Backlit)	Color IPS 320x240 (Backlit)	Color TFT 800x480 (Backlit)	Color TFT 800x480 (Backlit)	Color IPS 320x240 (Backlit)
	True RMS Sampling Rate	512	256	1024	1024	1024
	Battery-backed Real-time Clock	✓	✓	✓	✓	✓
	Operating Temperature (°C)	-25 to 70	-25 to 70	-25 to 70	-25 to 70	-25 to 70
Communications	Protocol	Modbus RTU, Modbus TCP, HTTP/HTTPS, NTP, SMTP, SNMP, FTP/FTPS, RSTP, MQTT, BACnet/IP, IEC61850, IEC60870-5-104	Modbus RTU, Modbus TCP, HTTPS, SNTP, SMTPS, FTPS, SNMP, Ethernet Gateway, BACnet/IP, IEC61850	Modbus RTU, Modbus TCP, HTTPS, NTP, SMTPS, SNMP, FTPS, Ethernet Gateway, MQTT, IPsec VPN and IEC61850, IEEE1588 (PTP)	Modbus RTU, Modbus TCP, HTTPS, SNTP, SMTPS, FTP, Ethernet Gateway, IEC61850, IEEE1588 (PTP)	Modbus RTU, Modbus TCP, HTTPS, NTP, SMTPS, FTPS, MQTT, IPsec VPN, Ethernet Gateway, IEC61850, IEEE1588 (PTP)
	RS-485 Port	1	1	1	2	1
	Ethernet port	2	1	2	2	2
	Web Server	✓	✓	✓	✓	✓
I/O	Digital Input (DI)	4	6	4 (8 Opt.)	8 (16 Opt.)	4
	Pulse Counter	✓	✓	✓	✓	✓
	Mechanical Digital Output (DO)/ Solid State Output (SS)	2DO or (2 Opt.)SS	3DO	3DO (Opt. 1DO +2SS or Opt. 5DO)	4DO+4SS (Opt. 8DO +4SS or 4DO+2SS)	3DO or (3 Opt.)SS
	Analog Input (AI), 0/4-20mA	-	(1 Opt.)	(2 Opt.)	(2 Opt.)	(2 Opt.)
	Analog Output (AO), 0/4-20mA	-	-	-	(1 or 2 Opt.)	-
	kWh & kvarh Pulse Output (LED)	✓	✓	✓	✓	✓
	kWh & kvarh Pulse Output	(2 Opt.)	-	2	4 (2 Opt.)	3
IRIG-B (GPS)	✓	✓	✓	✓	✓	
Measurements	ULN per Phase & Avg.	✓	✓	✓	✓	✓
	ULL per Phase & Avg.	✓	✓	✓	✓	✓
	Current per Phase & Avg.	✓	✓	✓	✓	✓
	Neutral Current (Meas./Calc.)	✓	✓	✓	✓	✓
	Frequency	✓	✓	✓	✓	✓
	kW per Phase & Total	✓	✓	✓	✓	✓
	kvar per Phase & Total	✓	✓	✓	✓	✓
	kVA per Phase & Total	✓	✓	✓	✓	✓
	PF per Phase & Total	✓	✓	✓	✓	✓
	kWh Import/Export	✓	✓	✓	✓	✓
	kvarh Import/Export	✓	✓	✓	✓	✓
	kVAh Total	✓	✓	✓	✓	✓
	Demands & TOU	✓	✓	✓	✓	✓
Maximum Demand	✓	✓	✓	✓	✓	
Setpoints	✓	✓	✓	✓	✓	
Power Quality	THD Voltage & Current	✓	✓	✓	✓	✓
	TOHD Voltage & Current	✓	✓	✓	✓	✓
	TEHD Voltage & Current	✓	✓	✓	✓	✓
	K-Factor	✓	✓	✓	✓	✓
	Individual Harmonics	2 <sup>nd</sup> - 63 <sup>rd</sup>	2 <sup>nd</sup> - 63 <sup>rd</sup>	2 <sup>nd</sup> - 63 <sup>rd</sup>	2 <sup>nd</sup> - 63 <sup>rd</sup>	2 <sup>nd</sup> - 63 <sup>rd</sup>
	Voltage/Current Unbalance	✓	✓	✓	✓	✓
	Waveform Capture on Screen	✓	✓	✓	✓	✓
	Waveform Recording	✓	✓	✓	✓	✓
	Dip Swell Detection	✓	✓	✓	✓	✓
	Transient Detection	✓	✓	✓	✓	✓
IEC61000-4-30	Ed. 3.1 Class S/A Compliant	Ed. 3 Class S Compliant	Ed. 3.1 Class A Certified	Ed. 3.1 Class A Certified	Ed. 3 Class A Certified	
2-150kHz Conducted Emission	2-9kHz only	-	Compliant	Compliant	Compliant	
Logs	SOE Log	512 entries	512 entries	1024 entries	1024 entries	1024 entries
	PQ Log	✓	✓	✓	✓	✓
	Energy Log	✓	✓	✓	✓	✓
	Max./Min. Log	✓	✓	✓	✓	✓
	On-board Log Memory	(4GB Opt.)	2GB	4GB	8GB	4GB

# Power Quality Monitors








Legend: (Opt.)-Optional (Via Comm.)-Via Communication (Meas./Calc.)-Measured Value/Calculated Value (Dmnd.)-Demand

	Key Features	PMC-53A-E	PMC-53A	PMC-53M-A	PMC-S963-E	PMC-S963-C	PMC-D726M	PMC-592	PMC-512-A
General	Class (kWh)	0.2S/0.5S	0.2S/0.5S	0.5S	0.5S	0.5S	1	0.5S	1
	Dimensions (WxHxD/mm)	 96x96x83.6	 96x96x83.6	 96x96x83.6	 96x96x92	 96x96x92	 72x72x76.8	 260.5x154x55.5	 126x90x65
	Display (Backlit)	Dot-Matrix LCD (Backlit)	Dot-Matrix LCD (Backlit)	B&W (Backlit)	B&W (Backlit)	B&W (Backlit)	B&W (Backlit)/LED	Optional Color TFT 800x480 (Backlit)	B&W (Backlit)
	True RMS Sampling Rate	128	128	128	64	64	64	64	64
	Battery-backed Real-time Clock	√	√	√	√	√	-	√	√
	Operating Temperature (°C)	-25 to 70	-25 to 70	-25 to 70	-25 to 70	-25 to 70	-25 to 70	-25 to 70	-25 to 70
	Voltage Input	400VLN/690VLL	400VLN/690VLL	400VLN/690VLL	400VLN/690VLL	400VLN/690VLL	400VLN/690VLL	277VLN/480VLL	240VLN/415VLL
	Current Input	5A (1A/SCCT Opt.)	5A (1A/SCCT Opt.)	5A/1A Auto-Scaling	5A/1A Auto-Scaling	5A/1A Auto-Scaling	5A (Optional 1A)	5A/1A (Main), 100-1600A (Branch)	5A, 50A-1600A
	Power Supply	60-250 VAC ± 10%, 47-440Hz, 24-250 VDC ± 10%	60-250 VAC ± 10%, 47-440Hz, 24-250 VDC ± 10%	60-250 VAC ± 10%, 47-440Hz, 24-250 VDC ±10%	95-250 VAC/DC, 47-440Hz	95/250V AC/DC, 47-440Hz	95/250V AC/DC, 47-440Hz	95-277VAC/DC, ± 10%, 47-440Hz	95-250VAC/VDC, 47-440Hz 20-60VDC
Communications	Protocol	Modbus RTU, Modbus TCP, HTTP, BACnet MS/TP, DNP 3.0, Ethernet Gateway, SNMP, SMTP, TFTP	Modbus RTU, BACnet MS/TP, Metasys N2 and DNP3.0	Modbus RTU	Modbus RTU, Modbus TCP, SNTP	Modbus RTU	Modbus RTU	Modbus RTU, Modbus TCP, SNMP, SNTP, SMTP, HTTP	Modbus RTU
	RS-485 Port	1	1 + (1 Opt.)	1	1	1	1	2	2
	Ethernet port	1	-	-	1	-	-	1	-
	Web Server	√	-	-	-	-	-	√	-
I/O	Digital Input (DI)	4	(6 Opt.)	(4 Opt.)	4	4	(2 Opt.)	2	12
	Pulse Counter	√	√	√	-	-	-	√	√
	Mechanical Digital Output (DO)/ Solid State Output (SS)	2DO or (2 Opt.)SS	(4 Opt.)DO or (2 Opt.)SS	(2 Opt.)DO	2×DO+1×SS	(2 Opt.)DO or (1 Opt.)SS	(2 Opt.)DO	2DO	1DO
	Analog Input (AI), 0/4-20mA	(1 Opt.)	(1 Opt.)	-	-	-	-	-	-
	Analog Output (AO), 0/4-20mA	-	1 or 2	-	-	(1 Opt.)	(1 Opt.)	-	-
	kWh & kvarh Pulse Output (LED)	√	√	√	√	√	√	√	√
	kWh & kvarh Pulse Output	(2 Opt.)	(2 Opt.)	-	1	1	-	-	-
IRIG-B (GPS)	-	-	-	-	-	-	-	-	
Measurements	ULN per Phase & Avg.	√	√	√	√	√	√	√	√
	ULL per Phase & Avg.	√	√	√	√	√	√	√	√
	Current per Phase & Avg.	√	√	√	√	√	√	√	√
	Neutral Current (Meas./Calc.)	√	√	(Calc.)	(Calc.)	(Calc.)	(Calc.)	Meas.	√
	Frequency	√	√	√	√	√	√	√	√
	kW per Phase & Total	√	√	√	√	√	√	√	√
	kvar per Phase & Total	√	√	√	√	√	√	√	√
	kVA per Phase & Total	√	√	√	√	√	√	√	√
	PF per Phase & Total	√	√	√	√	√	√	√	√
	kWh Import/Export	√	√	√	√	√	√	√	√
	kvarh Import/Export	√	√	√	√	√	√	√	√
	kVAh Total	√	√	√	√	√	√	√	√
	Demands & TOU	√	√	Dmd. Only	√	√	√	√	√
	Maximum Demand	√	√	√	√	√	√	√	√
Setpoints	√	√	√	√	√	√	√	√	
Power Quality	THD Voltage & Current	√	√	√	√	√	√	√	√
	TOHD Voltage & Current	√	√	√	√	√	√	√	√
	TEHD Voltage & Current	√	√	√	√	√	√	√	√
	K-Factor	√	√	√	-	-	√	√	√
	Individual Harmonics	2 <sup>nd</sup> - 63 <sup>rd</sup>	2 <sup>nd</sup> - 63 <sup>rd</sup>	2 <sup>nd</sup> - 63 <sup>rd</sup>	2 <sup>nd</sup> - 31 <sup>st</sup>	2 <sup>nd</sup> - 31 <sup>st</sup>	2 <sup>nd</sup> - 31 <sup>st</sup>	2 <sup>nd</sup> - 31 <sup>st</sup>	2 <sup>nd</sup> - 31 <sup>st</sup>
	Voltage/Current Unbalance	√	√	√	√	√	√	√	√
	Waveform Capture on Screen	√	√	-	-	-	-	-	-
	Waveform Recording	-	-	-	-	-	-	√	-
Dip Swell Detection	-	-	-	-	-	-	√	-	
Logs	SOE Log	100 entries	100 entries	100 entries	32 entries	32 entries	16 entries	1000 entries	512 entries
	PQ Log	-	-	-	-	-	-	-	-
	Energy Log	√	√	-	√	√	-	√	√
	Max./Min. Log	√	√	√	√	√	-	√	-
	On-board Log Memory	16MB	(16MB Opt.)	-	-	-	-	1GB	4MB






Legend: (Opt.)-Optional (Via Comm.)-Via Communication (Meas./Calc.)-Measured Value/Calculated Value (Dmd.)-Demand

# Multi-Function Panel Meters

## Multi-Circuit Monitors

Key Features		PMC-220	PMC-220-A6	PMC-230	PMC-340	PMC-340-A6	PMC-350-C	PMC-352-C
General	Class (kWh)	0.5	1	1	0.5 for 100A Direct Connected Input, 0.5S for 5A CT Input	0.5 for 100A Direct Connected Input, Class 0.5S for CT Input	1	1
	Dimensions (WxHxD/mm)	 36x90x65	 36x95x70	 72x90x68	 126x90x65	 72x95x70	 LoRaWAN 72x95x70	 LoRa 36x90x65
	Display (Backlit)	B&W (Backlit)	B&W (Backlit)	B&W (No Backlit)	B&W (No Backlit)	B&W (Backlit)	B&W (No Backlit)	-
	True RMS Sampling Rate	36	114	36	64	160	64	64
	Battery-backed Real-time Clock	-	√	√	√	√	√	-
	Voltage Input	95-264VAC	85-276VAC	95-264VAC	168-264VAC	88-276VAC	20-277V L-N/35-480V L-L	277VLN/480VLL 40V to 1.2Un
	Current Input (In/Imax)	5A/63A	5A/80A	5A/65A	20A/100A (Direct Connected Input) 5A/6A (CT Input)	10A/100A (Direct Connected Input) 1A/10A (CT Input)	5A/6A (CT Input), optional SCCT Input with 40mA or 2mA secondary	SCCT Input with 40mA or 2mA secondary
Operating Temperature (°C)	-25 to 70	-25 to 70	-25 to 70	-25 to 70	-25 to 70	-25 to 70	-25 to 70	
Communications	Protocol	Modbus RTU	Modbus RTU	Modbus RTU	Modbus RTU	Modbus RTU	Modbus RTU (Optional LoRaWAN support at RU864/IN865/EU868/US915/AU915/KR920/AS923-1/AS923-2/AS923-3/AS923-4)	Modbus RTU (Built-in LoRa with configurable ISM Bands for EU863-870, RU864-870, IN865-867, US902-928, AU915-928, AS920-923 and AS923-925)
	RS-485 Port	1	1	1	1	1	1	1
	Ethernet port	-	-	-	-	-	-	-
	Web Server	-	-	-	-	-	-	-
3-Level Comm. Password	-	√	√	-	√	-	-	
I/O	Digital Input (DI)	-	1 Opt.	3	(3 Opt.)	1 (Opt. for Direct Connected Input)	(4 Opt.)	3
	Pulse Counter	-	√	√	√	√	√	√
	Mechanical Digital Output (DO)/ Solid State Output (SS)	1SS	1SS Opt.	1SS	1SS	1 SS (Opt. for Direct Connected Input)	(2 Opt.)DO or (2 Opt.)SS	-
	Analog Input (AI), 0/4-20mA	-	-	-	-	-	-	-
	Analog Output (AO), 0/4-20mA	-	-	-	-	-	-	-
	kWh & kvarh Pulse Output (LED)	√	√	√	√	√	√	-
	kWh & kvarh Pulse Output	1	1 Opt.	1	1	1 Opt.	2	-
IRIG-B (GPS)	-	-	-	-	-	-	-	
Measurements	ULN per Phase & Avg.	1 phase only	1 phase only	1 phase only	√	√	√	√
	ULL per Phase & Avg.	-	-	-	√	√	√	√
	Current per Phase & Avg.	1 phase only	1 phase only	1 phase only	√	√	√	√
	Neutral Current (Meas./Calc.)	-	-	-	(Calc.)	(Calc.)	(Calc.)	-
	Frequency	√	√	√	√	√	√	√
	kW per Phase & Total	1 phase only	1 phase only	1 phase only	√	√	√	√
	kvar per Phase & Total	1 phase only	1 phase only	1 phase only	√	√	√	√
	kVA per Phase & Total	1 phase only	1 phase only	1 phase only	√	√	√	√
	PF per Phase & Total	1 phase only	1 phase only	1 phase only	√	√	√	√
	kWh Import/Export	√	√	√	√	√	√	√
	kvarh Import/Export	√	√	√	√	√	√	√
	kVAh Total	√	√	√	√	√	√	√
	Demands & TOU	-	√	√	√	√	√	Dmd. Only
Maximum Demand	-	√	√	√	√	√	-	
Setpoints	-	√	√	-	√	√	√	
Power Quality	THD Voltage & Current	-	-	√	√	√	√	√
	TOHD Voltage & Current	-	-	-	√	√	√	√
	TEHD Voltage & Current	-	-	-	√	√	√	√
	K-Factor	-	-	-	√	√	√	-
	Individual Harmonics	-	-	-	2 <sup>nd</sup> - 31 <sup>st</sup>	2 <sup>nd</sup> - 31 <sup>st</sup>	2 <sup>nd</sup> - 31 <sup>st</sup>	2 <sup>nd</sup> - 31 <sup>st</sup>
Voltage/Current Unbalance	-	-	-	√	√	√	√	
Logs	SOE Log	-	128 entries	64 entries	16 entries (Opt.)	128 entries	100 entries	16 entries
	Energy Log	-	√	√	√	√	√	-
	Max./Min. Log	-	-	-	√	√	√	-
	On-board Log Memory	-	16MB Opt.	4MB	(2MB Opt.)	16MB	4MB	8KB
	Data Recorder Log	-	2x65535 entries (Opt.)	√	√	√	√	-

Legend: (Opt.)-Optional (Via Comm.)-Via Communication (Meas./Calc.)-Measured Value/Calculated Value (Dmd.)-Demand

Key Features		PMC-1202	PMC-1302-3 (N & 7)	PMC-1302-3 (T)	iSmartGate SE	PMC-1304-3
General	Dimensions (WxHxD/mm)	 36x65x90	 72x90x61	 72x90x61	 36x65x90	 63x145x115
	Display (Backlit)	-	-	-	-	-
	Memory	4MB	16MB	16MB	8GB	2GB
	Built-in Web Interface	√	√	√	√	√
	Power Supply	95-250VAC/DC ± 10% or 12-36V DC	95-250VAC/DC ± 10% or 20-60VDC	95-250VAC/DC ± 10% or 20-60VDC	95-250VAC/DC ± 10% or 12-36V DC	95-250VAC/DC ± 10% or 20-60VDC Single PS or 20-60VDC Dual PS
	LED Indicator	5 Indicators 1 for Running Status 1 for Ethernet Comm. Status 1 for LoRa Comm. Status 2 for RS-485 Comm. Status	4 Indicators 1 for Running Status 1 for LoRa Comm. Status 2 for RS-485 Comm. Status	4 Indicators 1 for Running Status 1 for LoRa Comm. Status 2 for RS-485 Comm. Status	6 Indicators 1 for Running Status 2 for RS-485 Comm. Status 1 for 4G Comm. Status 1 for Ethernet Comm. Status 1 for LoRa Comm. Status	6 Indicators 1 for Running Status 1 for Alarm Status 2 or 4 for RS-485 Comm. Status
	Time Sync.	Modbus	Modbus	Modbus, RTC	SNTP, Modbus, RTC	SNTP, Modbus, optional GPS or IRIG-B
Type	Transparent Gateway	√	√	√	√	-
	Modbus TCP/RTU Gateway	√	√	√	√	√
	Protocol Gateway	-	-	√	√	√
	Multi Master	√	√	√	√	√
Ethernet Interface	10/100BaseT Port (RJ45 Connector)	1	1	1	1	2
	100/1000BaseX Fiber-optic port	-	-	-	-	-
	Isolation Protection	1.5kV	1.5kV	2kV	1.5kV	1.5kV
	Protocol	Modbus TCP Client/Server, UDP Client/Server, HTTP, WebSocket and HTTPD Client	Modbus TCP Client/Server, UDP Client/Server, HTTP	Modbus TCP Client/Server, UDP Client/Server, HTTP	Modbus TCP Client/Server, IEC 104 Client/Server, DHCP, Anypolling, MQTT+JSON, HTTP+JSON, AliCloud, Amazon AWS (4G), Optional BACnet/IP	Modbus TCP Client/Server, SFTP Client Support, HTTP
Serial Interface	RS-485 Port	2	2	2	2	2 or 4 (including 1xRS-422/RS-485)
	RS-232 Port	-	-	-	-	-
	Baudrate	600/1200/2400/4800/9600/ 19200/38400 bps	300/600/1200/2400/ 4800/9600/19200/38400bps	300/600/1200/2400/ 4800/9600/19200/38400bps	300/600/1200/2400/ 4800/9600/19200/38400bps	300/600/1200/2400/4800/9600/ 19200/38400/57600/115200 bps
	Isolation Protection	3kV	3kV	3kV	3kV	3kV
	Protocol	Modbus RTU	Modbus RTU	Modbus RTU	Modbus RTU, MQTT Client	Modbus RTU
Wireless Interface	4G	-	-	-	√	-
	LoRa	√	√	√	√	-
	Band Options	Configurable ISM Bands for EU863-870, RU864-870, IN865-867, US902-928, AU915-928, AS920-923 and AS923-925	Configurable ISM Bands for EU863-870, RU864-870, IN865-867, US902-928, AU915-928, AS920-923 and AS923-925	Configurable ISM Bands for EU863-870, RU864-870, IN865-867, US902-928, AU915-928, AS920-923 and AS923-925	Configurable ISM Bands for EU863-870, RU864-870, IN865-867, US902-928, AU915-928, AS920-923 and AS923-925	-
	Protocol	Modbus RTU Client/Server	Modbus RTU Client/Server	Auto-push private protocol for working with LoRa Temp. Sensors (PMC-2601 & 2603)	Modbus RTU Client/Server (LoRa) MQTT+JSON, HTTP+JSON, AliCloud, Amazon AWS (4G)	-
Logs	Data Recorder Logs	-	-	√	√	√
	SOE Logs	-	-	√	√	√
	Device Logs	-	-	-	√	-
Input/Output	DI	-	-	-	-	-
	DO	-	-	-	-	-
	AI	-	-	-	-	-
Environmental Mechanical &	Installation	DIN Rail	DIN Rail	DIN Rail	DIN Rail	DIN Rail or Panel Mounting
	Operating Temperature	-25°C to +70°C	-25°C to +70°C	-25°C to +70°C	-25°C to +70°C	-25°C to +70°C
	Humidity	5% to 95% non-condensing	5% to 95% non-condensing	5% to 95% non-condensing	5% to 95% non-condensing	5% to 95% non-condensing

# Intelligent Protection Relay

## LV Motor Protection Relay Features

Features		Model	PMC-550D	PMC-550D-H	PMC-550D-S	PMC-550A	PMC-550J-S	PMC-550J	PMC-550M-S2	
Metering	3-Ø Current & Phase Angle		■	■	■	■	■	■	■	
	3-Ø ULL and Phase Angle		■	■	■	■	■	■	■	
	IN & IR		■	■	■	■	■	■	■	
	kW/kvar		■	■	■	■	■	■	■	
	Power Factor/Frequency		■	■	■	■	■	■	■	
	Harmonics up to 31st		■	■	■	■	■	■	■	
Energy	kWh/kvarh		■	■	■	■	■	■	■	
Protection	Long Start		■	■	■	■	■	■	■	
	Phase Current Loss/Imbalance		■	■	■	■	■	■	■	
	Overcurrent/Thermal Overload		■	■	■	■	■	■	■	
	Jam		■	■	■	■	■	■	■	
	Short Circuit		■	■	■	■	■	■	■	
	Overload		■	■	■	■	■	■	■	
	Ground Fault		■	■	■	■	■	■	■	
	Under Load		■	■	■	■	■	■	■	
	Under Power		■	■	■	■	■	■	■	
	Undervoltage/Overvoltage		■	■	■	■	■	■	■	
	tE		■	■	■	■	■	■	■	
	Interlock		■	■	■	■	■	■	■	
	LOP Alarm		■	■	■	■	■	■	■	
	Residual Current		■	■	■	*	■	■	*	
	Thermal		*	*	N/A	■	■	N/A	N/A	
	Phase Reversal		■	■	■	■	■	■	■	
	Closed-loop Failure		■	■	■	■	■	■	■	
	Insulation Test		*	*	N/A	N/A	N/A	N/A	N/A	
	Control	Quick Restart		■	■	■	■	■	■	■
		Undervoltage Restart		■	■	■	■	■	■	■
Device Auto-Restart			■	■	■	■	■	■	■	
Start Control			■	■	N/A	N/A	■	■	N/A	
Direct-On-Line Start			■	■	■	■	■	■	■	
Reduced-Voltage Start			■	■	■	■	■	■	■	
FWD/REV, 2-speed Start			■	■	■	■	■	■	■	
VFD/Soft Starter		■	N/A	■	■	■	■	N/A		
Comm.	No. of Comm. Ports		2/3*	2	1	2	1/2*	1	1	
	Type C Port on Front Panel <sup>†</sup>		■	■	■	■	■	■	■	
	Modbus-RTU		■ (And TCP)	■	■	■	■	■	■	
	PROFIBUS-DP		*	*	N/A	*	*	*	*	
I/O	PROFINET		*	N/A	N/A	N/A	N/A	N/A	N/A	
	DI		10/12*	6	6	11/9*	8	8/6*	6/4*	
	DO		5/6*	4	4	6	5	5/4*	4/3*	
	AO		1*	1*	1*	1*	1*	1*	1*	
	Temperature		1/7*	6*	N/A	1*	1*/3*	N/A	N/A	

Notes:  
 ■ Supported | \* Optional | N/A Not Applicable  
<sup>†</sup>The type C port on the Front Panel supports Modbus RTU protocol through dedicated Type-C/RS-232 converter.

## LV Feeder Protection Relay Features

Features		Model	PMC-550F-2	PMC-550F-V	PMC-550F	PMC-550F-S2	
Metering	3-Ø Current		■	■	■	■	
	3-Ø Current Phase Angle		■	■	■	■	
	IN		■	■	■	■	
	IR		■	■	■	■	
	Current Unbalance		■	■	■	■	
	3-Ø ULN		■	■	N/A	N/A	
	ULN Phase Angle		■	■	N/A	N/A	
	3-Ø ULL		■	■	■	■	
	kW/kvar		■	■	■	■	
	Power Factor		■	■	■	■	
	Frequency		■	■	■	■	
	Harmonics up to 31st		■	■	■	■	
	Energy	kWh/kvarh		■	■	■	
	Protection	Instantaneous Overcurrent		■	■	■	■
Time Overcurrent			■	■	■	■	
Overcurrent			■	■	■	■	
IDMT Overcurrent			■	■	■	■	
Overload			■	■	■	■	
Neutral Overcurrent/ Ground Fault			■ (Meas./Cal.)	■ (Cal.)	■ (Cal.)	■ (Cal.)	
IDMT Neutral Overcurrent			■	■	N/A	■	
Negative Sequence			■	■	■	■	
Switch-Onto-Fault			■	■	■	■	
Current Imbalance			■	■	■	■	
Undervoltage			■	■	■	■	
Overvoltage			■	■	■	■	
Residual Current			*	*	■	*	
Control		SOE		128	128	128	128
		Waveform Recorder		16	16	16	16
		Run/Trip/Alarm LED		■	■	■	■
		Loss of Phase Voltage		■	■	■	■
	CB Spring Energy Storage Monitoring		■	■	■	■	
	Control Circuit Monitoring		■	■	■	■	
	Type C Port		■	■	■	N/A	
Comm.	Modbus RTU		■	■	■	■	
	PROFIBUS DP		*	*	N/A	N/A	
I/O	DI		8	8	6*/8*	6	
	DO		6	5	5*/4*	4	
	AO		1	1	1	1	
	Temperature		N/A	1*/3*	N/A	N/A	
Electrical Fire Monitoring	IR Monitoring		N/A	*	N/A	N/A	
	Temperature Monitoring		N/A	■	N/A	N/A	

Notes:  
 ■ Supported | \* Optional  
 N/A Not Applicable



# Our Services

CET has a team of dedicated and proficient Engineering Services personnel who are ready to provide expert assistance for your system deployment needs. We are committed to helping our customers create a more secure and reliable, energy conserving and environmentally friendly electrical power system. Our team of experts is prepared to provide customized solutions for your different application needs with timely and efficient services.

Please do not hesitate to contact our sales office or your local representative for more information.

---

Copyright © CET Inc. All rights reserved.



CONTACT

Telephone: 1300 194 337

Email: [hardwaresales@lpaenergygroup.com](mailto:hardwaresales@lpaenergygroup.com)

[www.lpaenergygroup.com](http://www.lpaenergygroup.com)

Your Local Representative

V.00 12.08.2025